

## V. DMX function:

Channel	Value	Function
CH1	0-255	Main dimming from dark to bright
CH2	0-255	Control strobe from slowly to quickly
CH3	0-50	No function
	51-100	Choose the color
	101-200	Color change by pulse
	201-240	Color change by Fade
	241-250	Color change by Snapping
	251-255	Sound control
CH4	0-255	The speed of function from slowly to quickly
CH5	0-255	Red dimming from dark to bright
CH6	0-255	Green dimming from dark to bright
CH7	0-255	Blue dimming from dark to bright
CH8	0-255	White/Amber dimming from dark to bright
CH9	0-255	Amber dimming from dark to bright

### Important notice:

- ✧ Before open the LED wall washer light and if you want to do the repair work, please make sure the power source is at the separation condition.
- ✧ Unceasingly carries on the product improvement about our company the policy, in this instruction booklet carries the data will have the possibility to be able to change in the future, when no longer separate notice change matters concerned. Our company retains when the product improvement changes the related specification the authority. This instruction booklet publisher cannot be responsible regarding this instruction booklet in information accuracy, also cannot the related consequence which causes regarding these information be responsible.

# LED WALL WASHER-6IN1

MJ-2410-5IN1



## User Manual

=====PROFESSIONAL LED LIGHTING=====

Thank you for choosing our LED wall washer light. For the sake of your safety, Please read and follow these instructions carefully and keep this manual in a safe place for future reference.

## I. Installation: .

1. In order to secure the safe installation of the light, always use it in the well-ventilated environment.
2. Always keep this light with a safe distance from any flammable materials.
3. Never install, dismantle and maintain this light when it is powered; and all work aforesaid must be conducted by professionals.
4. The packing list of this light is as follows:
  - 1) Light -----1pcs
  - 2)Power Cable-----1pcs
  - 3) User Manual-----1pcs

## II. Effect:

1. This light operation is very simple, Attractive appearance, Humanized design, Dim without flicker and shake, Energy-efficient, Durable. It is suitable for photography, television stations, stage, dance hall, KTV, bar, evening show.
2. The program of this light can automatically operate, sound, accept DMX512 signal control and be connected for use.

## III. Menu display function table:

Please press “Menu” button to choose function , and press “Enter” button to confirm.

No.	Display	Function
1	A001	A001—A512 (9 channel) press “UP” and “Down” button change the DMX address (Slave mode)
2	d001	d001—d512 (5 channel) press “UP” and “Down” button change the DMX address
3	CC00	CC01—CC99 (Color change by Snapping), press “UP” and “Down” button change the snapping speed

4	CP00	CP01—CP99 (Color change by Fade), press “UP” and “Down” button change the Fade speed
5	DE00	CC01—CC99 (Color change by Pulse), press “UP” and “Down” button change the pulse speed
6	BEB1	No function
7	R000	R000—R255 (Red dimming by hand)
8	G000	G000—G255 (Green dimming by hand)
9	B000	B000—B255 (Blue dimming by hand)
10	W000	W000—W255 (White/Amber dimming by hand)
11	Y000	Y000—Y255 (Amber dimming by hand)

## IV. Technical Parameters:

Voltage: AC100-240V, 50Hz-60Hz

Power Consumption: 270 Watts

LED: 18pcs 15W 5in1 LED

LED Current: 500mA / 1 pc

LED Beam Angle: 25°

LED Lifetime: 80,000-100,000 hours

Possible Color Combinations: RGBWA color mixing

Dimming: 0-100% with regulated constant color control

Operation Modes: DMX512, Sound, Internal Program, Master-slave

DMX Control: 5/9 Channels

Waterproof grade: IP 65

Maximum Ambient Temperature: 40° C

Gross Weight: 7.2 kg

Package Size: 1070 x 18 x 155mm



**WARNING**

**Please do NOT use the lamp under the water!**

**Please do NOT connect the power cable hand by hand over 5pcs**